

Range Extender

DMEX1

The Dome Range Extender is designed to improve communication between Z-Wave devices. It amplifies Z-Wave signals and increases the reach of your controller, ensuring your devices stay connected. The Extender has an LED light that works as a night light and can also act as an indicator in regular mode. The included suction cup lets you mount the Extender onto any smooth surface while using a micro USB power supply. All these features makes the Dome Range extender the perfect choice for your home.

- Compatible with all Z-Wave controllers as a binary switch
- Power on inclusion ensures easy one step installation
- Extends Z-Wave range by more than 400' in all six directions
- Z-Wave plus
- LED light has night-light mode or can be used as an indicator in regular mode
- Plug into wall outlet or power with micro USB
- Suction cup mount included

KEY FEATURES




ONE STEP INSTALLATION

Install in seconds



EXTENDS RANGE

Over 400' of range extension



NIGHT LIGHT

Night light On/Off Status

TECHNICAL SPECIFICATIONS

- Dimensions of main enclosure: 1.84 in x 1.01 in x 1.80 in (4.67 cm x 2.56 cm x 4.57 cm)
- Required tools: None
- Power supply: 100-120V ~ 60Hz, 30mA, or 5V DC
- Wireless protocol: Z-Wave
- Frequency Band: 916 MHz (US)
- Range: More than 400 ft in all 6 directions (line of sight)
- Reported data: Light on/off status
- Available modes: Night light, on/off light (regular mode)
- Button functionality: Inclusion, Exclusion, Factory default, Light on/off, mode change
- Operating Conditions: 32°F to 104°F (0°C to 40°C)